

Description

Modulating Apparatus, Mobile Communication System,  
Modulating Method, and Communication Method

5

Technical Field

The present invention relates to a modulating  
apparatus, a mobile communication system, a modulating  
method, and a communication method, and more  
10 particularly, to a modulating apparatus, a mobile  
communication system, a modulating method, and a  
communication method that can conform to the FCC rule  
to be enforced in 2005 without using a linear power  
amplifier.

15

Background Art

Conventionally, the Land Mobile Radio (LMR)  
system in the United States has extremely low spectrum  
efficiency because frequencies are allocated to  
20 respective channels at extremely wide channel spacing  
such as 25 kHz or 30 kHz. To improve this spectrum  
efficiency, the Federal Communications Commission  
(FCC) of the United States provided in the FCC rule  
that, from 1997, the channel spacing be changed to  
25 12.5 kHz that was half the conventional spectrum  
efficiency. Consequently, the LMR system was operated  
at the channel spacing of 25 kHz or 12.5 kHz. This  
change of the channel spacing is explained in the FCC  
Rule (Title 47 Code of Federal Regulations PART 90:  
30 Private Land Mobile Radio Services)).

To further improve the spectrum efficiency, in 2005, the FCC rule for changing the channel spacing to 6.25 kHz, which is half the present spectrum efficiency, will be enforced. Therefore, in  
5 accordance with the enforcement of the FCC rule in 2005, it is necessary to develop an LMR system that can be operated even at the channel spacing of 6.25 kHz.

The FCC rule to be enforced in 2005 provides, as  
10 conditions for the LMR system, that the LMR system have spectrum efficiency capable of operating one sound channel per 6.25 kHz band and have a transfer rate equal to or higher than 4800 bps per 6.25 kHz band. It is possible to allow the LMR system to  
15 operate one sound channel per 6.25 kHz band by adopting the FDMA (Frequency Division Multiple Access) system in the 6.25 kHz band or the 4-slot TDMA (Time Division Multiple Access) system in the 25 kHz band. In recent years, since it is a general practice to  
20 transmit character data and the like in addition to sound data, it is desirable that the LMR system to be developed for the enforcement of the FCC rule in 2005 is capable of communicating not only sound data but also character data and the like.

25 First, the FCC rule that sets the standard of the present LMR system applicable to the channel spacing of 12.5 kHz will be explained. The FCC rule (Title 47 Part 90.210: Emission masks) prescribes emission masks corresponding to respective bands. A  
30 mask D having characteristics shown in Table 1 below

and Figure 1 is stipulated for the 12.5 kHz band.

Table 1

Displacement Range	Frequency	Attenuation (dB)
$fd < 5.625 \text{ kHz}$		0
$5.625 \text{ kHz} < fd < 12.5 \text{ kHz}$		$7.27 (fd - 2.88)$
$fd > 12.5 \text{ kHz}$		70 or $50 + 10 \log_{10}(P)$ whichever the lesser ATT

5

In the table,  $fd$  is a displacement frequency range from a center frequency and is represented by a unit kHz.  $P$  is a transmission power and is represented by a unit W.

10 Most of the present LMR systems applicable to the channel spacing of 12.5 kHz transmit an analog sound signal after subjecting the analog sound signal to Frequency Modulation (FM modulation) (analog FM modulation). A sound band and a maximum frequency  
15 shift of the LMR systems are as shown in Table 2 below.

Table 2

Modulation System	FM Modulation
Sound Band	0.3 kHz to 3 kHz
Maximum Frequency Shift	$\pm 2.5 \text{ kHz}$ Shift

20 The modulation system (APCO P25 Phase 1 modulation system, hereinafter "P25-P1 modulation system"), which was examined as the Project 25 in the APCO (Association of Public Safety Communications

Officials) and, then, enacted as the standard (TIA102) by the TIA (Telecommunications Industry Association) is also used as a modulation system of the LMR system applicable to the channel spacing of 12.5 kHz. This modulation system is a system for transmitting a digital signal of a base band according to quaternary FSK modulation. A transmission rate, a symbol rate, a base band filter, and a nominal frequency shift of the modulation system are as shown in Table 3 below.

Table 3

Transfer Rate	9600 bps
Symbol Rate	4800 symbol/s
Base Band Filter	Transmission: A filter obtained by combining a filter having a Raised Cosine characteristic with $\alpha=0.2$ and a shaping filter Reception: An integrate and dump filter
Modulation System	Quaternary FSK Modulation
Nominal Frequency Shift	Shifts of $+3=+1.8$ kHz, $+1=+0.6$ kHz, $-1=-0.6$ kHz, and $-3=-1.8$ kHz for respective four symbol levels ( $\pm 3, \pm 1$ )

In measuring an emission spectrum at the time when the analog FM modulation system is used, the FCC rule provides, as a measurement condition, that a modulation frequency be set to 2.5 kHz and that the emission spectrum be measured by being modulated at a level increased by 16 dB from a modulation signal level at which 50% of a maximum frequency shift is obtained. A waveform of the emission spectrum set to

satisfy this condition and the emission mask (mask D) are shown in Figure 2. As shown in Figure 2, it is provided that the emission mask be substantially at the same level as a line of a high-order component of  
5 2.5 kHz.

A waveform of an emission spectrum measured using pseudo-random data as a modulation signal in the P25-P1 modulation system and the emission mask (mask D) are shown in Figure 3. Since the pseudo-random  
10 data is used as the modulation signal, as shown in Figure 3, the emission spectrum measured has a uniformly distributed spectrum shape and conforms to the mask D.

A waveform of an emission spectrum measured  
15 using data with symbols +3 and -3, that is, data with shifts +1.8 kHz and -1.8 kHz rather than the pseudo-random data and the emission mask (mask D) are shown in Figure 4. Since a symbol rate is 4800 symbol/s and a rectangular wave is shaped to a sine wave by a base  
20 band filter, the emission spectrum measured is equivalent to a spectrum subjected to FM modulation with a frequency shift of a certain value by a sine wave of 2.4 kHz. As shown in Figure 4, the emission spectrum measured has a peak at a frequency integer  
25 times as high as 2.4 kHz and third-order and fourth-order components of the emission spectrum slightly deviate from the mask D.

The FCC rule stipulates a mask E having a characteristic shown in Table 4 below and Figure 5 for  
30 the 6.25 kHz band.

Table 4

Displacement Range	Frequency	Attenuation (dB)
$f_d < 3.0 \text{ kHz}$		0
$3.0 \text{ kHz} < f_d < 4.6 \text{ kHz}$		65 or $30 + 16.67(f_d - 3)$ or $55 + 10 \log_{10}(P)$ whichever the lesser ATT
$f_d > 4.6 \text{ kHz}$		65 or $55 + 10 \log_{10}(P)$ whichever the lesser ATT

5           In order to adapt an emission spectrum to the mask E, the analog modulation FM modulation system is applied as the modulation system in one case and the P25-P1 modulation system is applied as the modulation system in another case. These cases will be examined.

10           In the past, when the channel spacing was revised from 25 kHz to 12.5 kHz, an emission spectrum could be adapted to the emission mask (mask D) stipulated by the FCC rule by changing a frequency shift in the analog modulation FM modulation system  
15           from the 5 kHz shift to the 2.5 kHz shift. A waveform of an emission spectrum measured by changing a frequency shift from the 2.5 kHz shift to the 1.25 kHz shift following this example (at a modulation frequency of 2.5 kHz) and the emission mask (mask E)  
20           are shown in Figure 6. As shown in Figure 6, obviously, the emission spectrum measured does not conform to the emission mask.

          A waveform in the case in which a transmission rate and a frequency shift were set to half as large

as those at a channel spacing of 12.5 kHz and pseudo-random data was used as a modulation signal in the P25-P1 modulation system and the emission mask (mask E) are shown in Figure 7. A waveform of an emission spectrum in the case in which data with a symbol alternately taking  $\pm 3$  was used as a modulation signal in the P25-P1 modulation system and the emission mask (mask E) are shown in Figure 8.

Since the emission spectrum shown in Figure 7 is uniformly distributed, the emission spectrum seemingly conforms to the emission mask. However, actually, as shown in Figure 8, the emission spectrum does not conform to the emission mask.

Simply by halving the parameters such as a transmission rate and a frequency shift of the modulation system currently applied to the LMR system applicable to the channel spacing of 12.5 kHz in this way, it is impossible to adapt the emission spectrum to the emission mask (mask E).

A case in which another modulation system is used for the LMR system to adapt an emission spectrum to an emission mask (mask E) will be explained. For example, a case in which a modulation system of the APCO P25 Phase 2 standard (hereinafter, "P25-P2 modulation system") is applied to the LMR system will be examined. This P25-P2 modulation system is a system in which a modulation system on a transmission side is changed to the  $\pi/4$ QPSK modulation system while keeping a data format of the P25-P1 modulation system as it is. A transmission rate, a symbol rate, a base

band filter, and a phase shift of this modulation system are as shown in Table 5 below.

Table 5

5

Transmission Rate	9600 bps
Symbol Rate	4800 symbol/s
Base Band Filter	Transmission: A filter having a Raised Cosine characteristic with $\alpha=0.2$ Reception: An integrate and dump filter
Modulation System	$\pi/4$ QPSK modulation
Phase Shift	Shifts of $+3=+3/4p$ , $+1=+1/4p$ , $-1=-1/4p$ , and $-3=-3/4p$ for respective four symbol levels ( $\pm 3$ , $\pm 1$ )

A waveform of an emission spectrum measured when pseudo-random data was modulated by the P25-P2 modulation system and the emission mask (mask E) are shown in Figure 9. Since the P25-P2 modulation system is based on the  $\pi/4$ QPSK modulation system, as shown in Figure 9, the emission spectrum measured has a characteristic of steeply attenuating out of a band and conforms to the emission mask (mask E) despite the fact that the transmission rate is 9600 bps.

However, since the  $\pi/4$ QPSK modulation system is a linear modulation system, problems described below occur.

It is impossible to use a nonlinear power amplifier used in the present LMR system. In order to use a linear power amplifier in the LMR system, since an additional circuit such as a linearizer is required,



a space and cost for the LMR system increase. Since the linear power amplifier has lower efficiency and a larger consumed current compared with the nonlinear power amplifier, heat generation in a radio apparatus constituting the LMR system causes a problem. Moreover, in a portable LMR system, since the portable LMR system is driven by a battery, an operation time decreases.

At this moment, a linear power amplifier having an output power that is the same as that of the conventional nonlinear power amplifier and having efficiency equivalent to that of the conventional nonlinear power amplifier has not been developed. In addition, it is extremely difficult to make a mounting space and cost of a nonlinear power amplifier equivalent to those of the non-linear power amplifier. Therefore, it is not realistic to apply the linear modulation system represented by the P25-P2 modulation system to the LMR system applicable to the channel spacing of 6.25 kHz.

The invention has been devised to solve the problems and it is an object of the invention to provide a modulating apparatus, a mobile communication system, a modulating method, and a communication method that can conform to the FCC rule to be enforced in 2005 without using a linear power amplifier.

#### Disclosure of the Invention

In order to attain the object of the invention, the invention provides a modulating apparatus in a

mobile communication system that performs data communication at a rate for transmitting 2400 multi-value symbols per second. This modulating apparatus includes: a base band filter that blocks an unnecessary frequency component of a multi-value symbol inputted and outputs a waveform signal; and frequency shifting and modulating means for shifting to modulate a frequency of an output signal according to a magnitude of an amplitude of the waveform signal inputted from the base band filter. The frequency shifting and modulating means is adjusted such that, when a symbol having a maximum absolute value is inputted, an output signal has an absolute value of a frequency shift in a range of 0.822[kHz] to 0.952[kHz].

15 In order to attain the object, a modulating apparatus according to a first aspect of the invention is a modulating apparatus in a mobile communication system that performs data communication at a transmission rate of  $2400 \times (n+1)$  (n: natural number) [bps]. The modulating apparatus includes: symbol converting means for sequentially converting a binary signal generated by encoding predetermined data into a  $2^{(n+1)}$ -ary symbol, which includes  $(2^{(n+1)}+1-2k)$  ( $1 \leq k \leq 2^{(n+1)}$ ) values, (n+1) bits at a time and outputting the symbol; a base band filter that blocks an unnecessary frequency component of a symbol inputted from the symbol converting means and outputs a waveform signal; and frequency shifting and modulating (FM) means for shifting to modulate a frequency of an output signal according to a magnitude of an amplitude

of the waveform signal inputted from the base band filter. When a symbol of  $\pm(2^{(n+1)}-1)$  is outputted from the symbol converting means, a frequency shift of the output signal from the frequency shifting and  
5 modulating means is set to take a value in a range of  $\pm 0.822[\text{kHz}]$  to  $\pm 0.952[\text{kHz}]$ .

In the modulating apparatus, the base band filter may be a Nyquist filter.

In order to attain the object, a mobile  
10 communication system according to a second aspect of the invention is a mobile communication system including: a transmitter that performs transmission of data at a transmission rate of  $2400 \times (n+1)$  ( $n$ : natural number) [bps]; and a receiver that receives data  
15 transmitted from the transmitter. The transmitter includes: encoding means for encoding predetermined data to generate a binary signal; symbol converting means for sequentially converting a binary signal generated by the encoding means into a  $2^{(n+1)}$ -ary symbol,  
20 which includes  $(2^{(n+1)}+1-2k)$  ( $1 \leq k \leq 2^{(n+1)}$ ) values,  $(n+1)$  bits at a time and outputting the symbol; a first base band filter that blocks an unnecessary frequency component of a symbol inputted from the symbol converting means and outputs a waveform signal; and  
25 frequency shifting and modulating (FM) means for transmitting a signal, which is obtained by shifting to modulate a frequency according to a magnitude of an amplitude of the waveform signal inputted from the first base band filter, to the receiver. The receiver  
30 includes: demodulating means for demodulating the

signal transmitted from the transmitter and received  
and outputting a  $2^{(n+1)}$ -ary signal; a second base band  
filter that blocks an unnecessary frequency component  
of the  $2^{(n+1)}$ -ary signal outputted from the demodulating  
5 means and outputs the  $2^{(n+1)}$ -ary signal; binary signal  
converting means for sequentially converting a  $2^{(n+1)}$ -  
ary signal inputted from the second base band filter  
into a binary signal of  $(n+1)$  bits and outputting the  
binary signal; and decoding means for decoding a  
10 binary signal inputted from the binary signal  
converting means and outputting the predetermined data.  
When a symbol of  $\pm(2^{(n+1)}-1)$  is outputted from the  
symbol converting means, a frequency shift of a signal  
outputted from the frequency shifting and modulating  
15 means is set to take a value in a range of  $\pm 0.822[\text{kHz}]$   
to  $\pm 0.952[\text{kHz}]$ .

In the mobile communication system, the first  
and second base band filters may be Nyquist filters.

In the mobile communication system, the first  
20 base band filter may include a root raised cosine  
filter and a sinc filter. The second base band filter  
includes a root raised cosine filter and a  $1/\text{sinc}$   
filter that has a characteristic opposite to that of  
the sinc filter. A nominal frequency shift of the  
25 symbol of  $\pm(2^{(n+1)}-1)$  may be set to a value  $\pi/2\sqrt{2}$  times  
as large as a frequency shift of a signal outputted  
from the frequency shifting and modulating means.

Moreover, in the mobile communication system,  
the first and second base band filters may include  
30 root raised cosine filters. The nominal frequency

shift of the symbol of  $\pm(2^{(n+1)}-1)$  may be set to a value  $1/\sqrt{2}$  times as large as a frequency shift of a signal outputted from the frequency shifting and modulating means.

5           In the mobile communication system, the first base band filter may include a raised cosine filter and a  $1/\text{sinc}$  filter. The second base band filter may include a sinc filter that has a characteristic opposite to that of the  $1/\text{sinc}$  filter. The nominal  
10 frequency shift of the symbol of  $\pm(2^{(n+1)}-1)$  may be set to a value  $2/\pi$  times as large as a frequency shift of a signal outputted from the frequency shifting and modulating means.

          In order to attain the object, a modulating  
15 method according to a third aspect of the invention is a modulating apparatus in a mobile communication system that performs data communication at a transmission rate of  $2400 \times (n+1)$  ( $n$ : natural number) [bps]. The modulating method includes: a symbol  
20 converting step of sequentially converting a binary signal generated by encoding predetermined data into a  $2^{(n+1)}$ -ary symbol, which includes  $(2^{(n+1)}+1-2k)$  ( $1 \leq k \leq 2^{(n+1)}$ ) values,  $(n+1)$  bits at a time and outputting the symbol; a step of blocking an unnecessary  
25 frequency component of a symbol inputted at the symbol converting step and outputting a waveform signal; and a frequency shifting and modulating (FM) step of shifting to modulate a frequency of an output signal according to a magnitude of an amplitude of the  
30 waveform signal inputted. When a symbol of  $\pm(2^{(n+1)}-1)$

is outputted from the symbol converting step, a frequency shift of the output signal from the frequency shifting and modulating step is set to take a value in a range of  $\pm 0.822$ [kHz] to  $\pm 0.952$ [kHz].

5           In order to attain the object, a communication method according to a fourth aspect of the invention is a communication method in a mobile communication system including: a transmitter that performs transmission of data at a transmission rate of  
10  $2400 \times (n+1)$  ( $n$ : natural number) [bps]; and a receiver that receives data transmitted from the transmitter. The communication method includes: an encoding step of encoding predetermined data to generate a binary signal; a symbol converting step of sequentially  
15 converting a binary signal generated by the encoding step into a  $2^{(n+1)}$ -ary symbol, which includes  $(2^{(n+1)}+1-2k)$  ( $1 \leq k \leq 2^{(n+1)}$ ) values,  $(n+1)$  bits at a time and outputting the symbol; a step of blocking an unnecessary frequency component of a symbol inputted  
20 from the symbol converting step and outputting a waveform signal; a frequency shifting and modulating (FM) step of transmitting a signal, which is obtained by shifting to modulate a frequency according to a magnitude of an amplitude of the waveform signal  
25 inputted from the first base band filter, to the receiver; a demodulating step of demodulating the signal transmitted from the transmitter and received and outputting a  $2^{(n+1)}$ -ary signal; a step of blocking an unnecessary frequency component of the  $2^{(n+1)}$ -ary  
30 signal outputted from the demodulating step and

outputting the  $2^{(n+1)}$ -ary signal; a binary signal  
converting step of sequentially converting a  $2^{(n+1)}$ -ary  
signal inputted into a binary signal of  $(n+1)$  bits and  
outputting the binary signal; and a decoding step of  
5 decoding a binary signal inputted from the binary  
signal generating step and outputting the  
predetermined data. When a symbol of  $\pm(2^{(n+1)}-1)$  is  
outputted from the symbol converting step, a frequency  
shift of a signal outputted from the frequency  
10 shifting and modulating step is set to take a value in  
a range of  $\pm 0.822[\text{kHz}]$  to  $\pm 0.952[\text{kHz}]$ .

#### Brief Description of the Drawings

Figure 1 is a graph showing a characteristic of  
15 a mask D;

Figure 2 is a graph showing a waveform of an  
emission spectrum in the case in which an analog FM  
modulation system is used and the mask D;

Figure 3 is a graph showing a waveform of an  
20 emission spectrum in the case in which pseudo-random  
data is converted in a P25-P1 modulation system and  
the mask D;

Figure 4 is a graph showing a waveform of an  
emission spectrum in the case in which symbols of  $\pm 3$   
25 are alternately generated in the P25-P1 modulation  
system and the mask D;

Figure 5 is a graph showing a characteristic of  
a mask E;

Figure 6 is a graph showing a waveform of an  
30 emission spectrum in the case in which the analog FM

modulation system is used and the mask E;

Figure 7 is a graph showing a waveform of an emission spectrum in the case in which a transmission rate and a frequency shift in the P25-P1 modulation system are halved and pseudo-random data is modulated and the mask E;

Figure 8 is a graph showing a waveform of an emission spectrum in the case in which a transmission rate and a frequency shift in the P25-P1 modulation system are halved and symbols of  $\pm 3$  are alternately generated and the mask E;

Figure 9 is a graph showing a waveform of an emission spectrum in the case in which pseudo-random data is modulated in a P25-P2 modulation system and the mask E;

Figure 10 is a graph showing an error rate characteristic in the case in which respective candidate filters are used;

Figure 11 is a graph showing an error rate characteristic in the case in which respective candidate filters are used;

Figure 12 is a block diagram showing a constitution of a ground mobile communication system according to a first embodiment of the invention;

Figure 13 is a flowchart for explaining operations of the ground mobile communication system according to the first embodiment;

Figure 14 is a graph showing a waveform of an emission spectrum in the case in which symbols of  $\pm 3$  are alternately generated in the ground mobile



communication system according to the first embodiment and the mask E;

Figure 15 is a graph showing a waveform of an emission spectrum in the case in which pseudo-random data is modulated in the ground mobile communication system according to the first embodiment and the mask E;

Figure 16 is a block diagram showing a constitution of a ground mobile communication system according to a second embodiment of the invention;

Figure 17 is a graph showing a waveform of an emission spectrum in the case in which symbols of  $\pm 3$  are alternately generated in the ground mobile communication system according to the second embodiment and the mask E;

Figure 18 is a graph showing a waveform of an emission spectrum in the case in which pseudo-random data is modulated in the ground mobile communication system according to the second embodiment and the mask E; and

Figure 19 is a block diagram showing a constitution of a ground mobile communication system according to a modification of the invention.

## Best Mode for Carrying Out the Invention

Embodiments of the invention will be hereinafter explained in detail with reference to the drawings.

As described above, it is impossible to adapt an emission spectrum to an emission mask (mask E) simply by halving parameters such as a transmission rate and

a frequency shift of a modulation system currently applied to an LMR system applicable to a channel spacing of 12.5 kHz. It is realistically difficult to use a linear modulation system represented by a P25-P2  
5 modulation system because of cost and the like.

Thus, in the embodiments described below, parameters such as a transmission rate and a frequency shift that can realize an LMR system conforming to the FCC rule to be enforced in 2005 by adopting a  
10 nonlinear modulation system represented by a quaternary FSK modulation system will be examined.

It is known that a spectrum of an FM modulation wave at the time when a modulation signal is a sine wave is represented by a Bessel function indicated by  
15 Expression (1) below.

$$\begin{aligned} \phi_{FM}(t) = & A [ J_0(mf) \cos \omega_c t + J_1(mf) \{ \cos(\omega_c + \omega_m)t - \cos(\omega_c - \omega_m)t \} \\ & + J_2(mf) \{ \cos(\omega_c + 2\omega_m)t - \cos(\omega_c - 2\omega_m)t \} \\ & + J_3(mf) \{ \cos(\omega_c + 3\omega_m)t - \cos(\omega_c - 3\omega_m)t \} + \dots ] \\ & \dots (1) \end{aligned}$$

20 where,  $\omega_c$  is a frequency of a carrier wave,  $\omega_m$  is a modulated frequency,  $mf$  is a modulation index (a frequency shift/a modulation frequency), and  $J_n(mf)$  is a Bessel function of the first kind for an  $n$ th order component.

25 Correlation between the emission spectrum shown in Figure 2 and the Bessel function indicated by Expression (1) is calculated. Since a modulation frequency is 2.5 kHz and a frequency shift is a 2.5 kHz shift, the modulation index  $mf$  is 1. When primary  
30 to quaternary components are calculated according to

the Bessel function, the following levels are obtained.

$$(\text{Primary}) = J_1(1) = -7.13 \text{ dB}$$

$$(\text{Secondary}) = J_2(1) = -18.79 \text{ dB}$$

$$(\text{Third-order}) = J_3(1) = -34.17 \text{ dB}$$

5       $(\text{Fourth-order}) = J_4(1) = -52.12 \text{ dB}$

When these values and values of peak spectra generated at frequencies integer times as high as 2.5 kHz in Figure 2 are compared, errors thereof are within a range of  $\pm 1$  dB. Therefore, a mission  
10 spectrum of an FM modulation wave using a sine wave for a modulation signal may be calculated by Expression (1).

A frequency shift conforming to this mask is calculated backward from a value of the mask E  
15 stipulated in the FCC rule. A stipulated level of the mask E in the secondary component is calculated as -65 dB from Figure 5. A modulation index  $m_f$  for setting an emission spectrum to be equal to or lower than this level is calculated as 0.067 by backward calculation.  
20 A frequency shift in this case is an extremely small value of  $0.067 \times 2.5 = 0.167$  kHz.

A general S/N (Signal/Noise) of an LMR system that is applicable to the channel spacing of 12.5 kHz and uses the frequency shift of 2.5 kHz is about 45 dB.  
25 When the frequency shift is halved, the S/N falls by 6 dB. Thus, an S/N at the time when a frequency shift is 0.167 kHz is calculated as  $45 + 20 \times \log_{10}(0.167/2.5) = 21.5$  dB. This clearly indicates performance that cannot stand a practical use.

30      Consequently, although it is possible to adopt a

frequency shift by reducing the frequency shift using the analog FM modulation, since performance cannot be permitted in terms of a practical use, this method is excluded from an object of examination.

5       A condition under which the LMR system adopting the quaternary FSK modulation system conforms to the FCC rule to be enforced in 2005 will be explained.

      In Figures 3 and 4, an emission spectrum in the case in which the P25-P1 modulation system is adopted is shown. In the case of digital modulation, a spectrum of a modulation wave is different depending on a characteristic of a data sequence used. As is evident from Figures 3 and 4, if random data is used, the spectrum disperses and average energy per unit frequency decreases. Thus, the spectrum is seemingly narrowed. In repetition of specific data, an emission spectrum is equivalent to a spectrum subjected to modulation with a sine wave. Since energy concentrates on components integer times as large as the sine wave, a wide spectrum is obtained. Therefore, a worst condition in the quaternary FSK modulation is a condition at the time when symbols of +3 and -3 with a wider frequency shift are used and the symbols are alternately repeated to subject an emission spectrum to modulation with a sine wave equal to a frequency half as high as a symbol rate.

      As described above, the FCC rule to be enforced in 2005 provides, as a condition, that an emission spectrum be adapted to the mask E and that, in performing transmission of data, an LMR system have a

transmission rate equal to or higher than 4800 bps per 6.25 kHz band. Thus, a frequency shift for adapting an emission spectrum to the mask E at the time when the quaternary FSK modulation system is used at a transmission rate of 4800 bps is calculated backward. In this case, since a symbol rate is 2400 symbol/s that is half the transmission rate of 4800 bps. Thus, by repeating symbols of +3 and -3, an emission spectrum is equivalently a sine wave of 1.2 kHz.

When a standard value of the mask E and a value of a spectrum integer times as large as 1.2 kHz are compared, a fourth order is most strict in terms of a condition. If this condition is satisfied, it is possible to adapt the emission spectrum to the mask E.

In this case, the modulation index  $m_f$  is 0.685 and a frequency shift takes a value indicated by Expression (2) below.

$$0.685 \times 1.2 = 0.822 \text{ kHz} \quad \dots (2)$$

As described above, the emission spectrum shown in Figure 4 does not conform to the mask D. The emission spectrum shown in Figure 4 is measured under the worst condition in the P25-P1 modulation system.

Following this example, an emission spectrum does not have to conform to an emission mask under the worst condition. In an actual state of use in which a sound signal is digitized and transmitted, since a data sequence shows a random characteristic, a spectrum in the actual state of use has a characteristic

substantially the same as that at the time when pseudo-random data is modulated. Therefore, under the worst condition, nonconformity may be allowed to some extent. An emission spectrum only has to completely  
5 conform to an emission mask when the pseudo-random data is used.

Levels of respective peak spectra under the worst condition at the time when the P25-P1 modulation system is adopted are calculated from the Bessel  
10 function. A degree of deviation of a spectrum from the mask D is calculated.

The base band filter represented by Table 3 includes a raised cosine filter and a shaping filter. A characteristic of this shaping filter is equal to a  
15 characteristic opposite to a characteristic of  $\text{sinc}(\sin(x)/x)$  in which an amplitude is 1 at a frequency of 0 and is 0 at a symbol frequency. Nominal frequency shifts in the symbols of +3 and -3 are +1.8 kHz and -1.8 kHz, respectively. In the  
20 raised cosine filter, since intersymbol interference does not occur, an amplitude of a symbol at a filter output does not change. Therefore, frequency shifts at the time when the symbols of +3 and -3 are alternately sent are equal to the nominal frequency  
25 shifts when only the raised cosine filter is used. Since a frequency characteristic of the shaping filter is equal to a characteristic opposite to that of sinc, the frequency characteristic is indicated by Expression (3) below.

$$\left( \begin{array}{l} \text{Characteristic of} \\ \text{the shaping filter} \end{array} \right) = \frac{1}{\text{sinc}} = \frac{f\pi / 4.8}{\sin(f\pi / 4.8)} \dots (3)$$

When the symbols of +3 and -3 are repeated, a frequency  $f$  is 2.4 kHz. When the frequency  $f$  is substituted in Expression (3), a characteristic of the shaping filter is  $\pi/2$ . Since an actual frequency shift changes by a degree equivalent to the characteristic of the shaping filter ( $=\pi/2$ ) from the nominal frequency shifts, an actual frequency shift of the filter including the raised cosine filter and the shaping filter is  $1.8 \text{ kHz} \times \pi/2 = 2.827 \text{ kHz}$ . Values of the Bessel function at the time when a modulation frequency is set to 2.4 kHz and a frequency shift is set to 2.827 kHz and values of the mask  $D$  calculated from Table 1 are shown in Table 6 below.

Table 6

Order	Frequency	Standard Value of Mask D	Bessel Function Value
1	2.4 kHz	0 dB	-6.15 dB
2	4.8 kHz	0 dB	-16.25 dB
3	7.2 kHz	-31.41 dB	-30.11 dB
4	9.6 kHz	-48.85 dB	-46.60 dB
5	12.0 kHz	-66.30 dB	-65.07 dB

As shown in Table 6, in components of third order and higher orders, values of the Bessel function are below the standard by about 1 dB to 2 dB. When the values of the Bessel function shown in Table 6 and the values of the respective peak spectra shown in

Figure 4 are compared, although there is a slight error, the values of the Bessel function and the values of the peak spectra are substantially correlated. Therefore, since the frequency shift 0.822 kHz indicated by Expression (2) is a frequency shift completely conforming to the mask E under the worst condition, if a slight fall below the standard is allowed under the worst condition as in the P25-P1 modulation system, a frequency shift equal to or larger than 0.822 kHz may be used. Taking into account the fact that an error rate in the FSK modulation system such as the P25-P1 modulation system depends on a frequency shift, it is advisable to set the frequency shift as large as possible. Thus, a value of a spectrum having a frequency integer times as large as 1.2 kHz calculated from the Bessel function and the standard value of the mask E are compared and, when an emission spectrum does not conform to the mask E under the worst condition but pseudo-random data is used, the modulation index  $m_f$  conforming to the mask E is 0.793 and a frequency shift takes a value indicated by Expression (4) below.

$$0.793 \times 1.2 = 0.952 \text{ kHz} \quad \dots (4)$$

Values of the Bessel function at the time when a modulation frequency is set to 1.2 kHz and a frequency shift is set to 0.952 kHz and values of the mask E calculated from Table 4 are shown in Table 7 below.



Table 7

Order	Frequency	Standard Value of Mask E	Bessel Function Value
1	1.2 kHz	0 dB	-8.72 dB
2	2.4 kHz	0 dB	-22.54 dB
3	3.6 kHz	-40.0 dB	-40.00 dB
4	4.8 kHz	-65.0 dB	-60.00 dB

The modulation index  $m_f=0.793$  is a modulation index at which a standard value of the mask E and a value of the Bessel function are the same in the third-order component. In the fourth-order component, a value of the Bessel function is below a standard value of the mask E by 5 dB. As shown in Table 4, in a frequency band of  $f_d > 4.6$  kHz, a standard value of the mask E changes according to a value of a transmission power P. When the transmission power P is equal to or higher than 10 W, a standard value is -65 dB. When the transmission power P is 5 W, a standard value is -62 dB. In general, in a portable radio apparatus, a transmission power is 5 W and, under this condition, a value of the Bessel function is below a standard value of the mask E by 3 dB. When the fall below the standard value of this degree is not significantly different from the fall below the standard with respect to the mask D in the case in which the P25-P1 modulation system is adopted shown in Table 6. Thus, it can be said that the fall below the standard is within a tolerance as in the case of the mask D.

In the above explanation, a maximum frequency

shift for adapting an emission spectrum to the mask E at the time when the quaternary FSK is used at the transmission rate of 4800 bps is calculated. When digital data is modulated, it is a well-known fact  
5 that a waveform is shaped using a base band filter. An error rate is affected by a base band filter used. As indicated by Expression (3), an actual frequency shift outputted from a modulator changes depending on a base band filter. Thus, nominal frequency shifts at  
10 the symbol levels of +3 and -3 obtained by calculating backward the maximum frequency shift 0.952 kHz indicated by Expression (4) are different.

It is a general practice to use a Nyquist transmission path as a transmission path in order to  
15 hold down an error rate. Therefore, in this embodiment, a Nyquist filter is used in a base band filer. An FM modulator and an FM demodulator have transparency as long as distortion does not occur. Thus, in order to form a Nyquist transmission path,  
20 the Nyquist filter only has to be arranged at a pre-stage of the FM modulator or a post stage of the FM demodulator such that the base band filter has a Nyquist characteristic. Since the shaping filter and the integrate and dump filter described in Table 3  
25 have opposite frequency characteristics, it can be understood that, if the modulator and the demodulator are integrated, only the raised cosine filter is left and that the Nyquist transmission path is formed.

As described above, it is a necessary condition  
30 that a Nyquist filter is used in order to reduce an

error rate. In addition, a nominal frequency shift at which an actual frequency shift of 0.952 kHz is obtained is different depending on a Nyquist filter used. Therefore, it is necessary to select a Nyquist filter with which a largest nominal frequency shift is obtained. In general, a filter having a raised cosine characteristic is used as a Nyquist filter. Combinations of filters in this case are shown in Table 8 below.

10

Table 8

Combination	Transmission Side	Reception Side
I	Raised Cosine	None
II	Raised Cosine + 1/sinc	sinc
III	None	Raised Cosine
IV	sinc	Raised Cosine + 1/sinc
V	Root Raised Cosine	Root Raised Cosine
VI	Root Raised Cosine + 1/sinc	Root Raised Cosine + sinc
VII	Root Raised Cosine + sinc	Root Raised Cosine + 1/sinc

Since a 1/sinc filter has a characteristic opposite to that of a sinc filter, the 1/sinc filter has a diverging frequency characteristic. Therefore, it is impossible to use the 1/sinc filter alone and a combination using only the 1/sinc filter is excluded. When no filter is provided on the reception side, since band limitation is not applied to noise and an S/N is deteriorated, an error rate extremely worsens. When no filter is provided on the transmission side, a

20

rectangular wave is directly subjected to FM modulation. A spectrum expands infinitely and does not conform to the mask E. Consequently, among the combinations, the combination I and the combination  
5 III are excluded from objects. Since the combination IV only has the sinc filter on the transmission side, band limitation is loose and spread of a spectrum is relatively large. Thus, the combination IV is also excluded from objects. Therefore, the four kinds of  
10 combinations II, V, VI, and VII are left as candidates.

A nominal frequency shift for setting an actual maximum frequency shift to 0.952 kHz when the candidate filters are used is calculated. A symbol rate is 2400 symbol/s and, in repetition of the  
15 symbols of +3 and -3, a spectrum is a sine wave of a frequency 1.2 kHz. When the raised cosine filter is used, a nominal frequency shift and an actual frequency shift are equal. When amplitudes in the respective filters at the frequency 1.2 kHz are  
20 calculated with an amplitude in this case as a reference value, the amplitudes are calculated as indicated by Expressions (5), (6), and (7) below.

(Amplitude of Raised Cosine) = 0.5 (Reference  
25 value) ... (5)

(Amplitude of Root Raised Cosine) =  $\sqrt{0.5}$  ... (6)

(Amplitude of sinc) =  $\frac{\sin(\pi \times 1.2 / 2.4)}{(\pi \times 1.2 / 2.4)} = \frac{2}{\pi}$  ... (7)

From these expressions, amplitude scaling

factors based on an amplitude in the raised cosine filter at 1.2 kHz of the four kinds of candidate filters are indicated by Expressions (8), (9), (10), and (11) below.

5

Candidate II: (Amplitude of Raised Cosine + 1/sinc) =  
 $1/(2/\pi) = \pi/2 \dots (8)$

Candidate V : (Amplitude of Root Raised Cosine) =  
 $\sqrt{0.5} / 0.5 = \sqrt{2} \dots (9)$

Candidate VI : (Amplitude of Root Raised Cosine + 1 / sinc) =  
 $\sqrt{2} \times \pi / 2 = \pi / \sqrt{2} \dots (10)$

Candidate VII : (Amplitude of Root Raised Cosine + sinc) =  
 $\sqrt{2} \times 2 / \pi \dots (11)$

10 In order to set an actual maximum frequency shift to 0.952 kHz, nominal frequency shifts in the respective candidate filters are calculated as indicated by Expressions (12), (13), (14), and (15).

Candidate II: (Shift of Raised Cosine + 1/sinc) =  
15  $0.952/(\pi/2) = 0.6061 \text{ kHz} \dots (12)$

Candidate V : (Shift of Root Raised Cosine) =  
 $0.952 / \sqrt{2} = 0.6732 \text{ kHz} \dots (13)$

Candidate VI : (Shift of Root Raised Cosine + 1 / sinc) =  
 $0.952 / (\pi / \sqrt{2}) = 0.4286 \text{ kHz} \dots (14)$

Candidate VII : (Shift of Root Raised Cosine + sinc) =  
 $0.952 / (\sqrt{2} \times 2 / \pi) = 1.0574 \text{ kHz} \dots (15)$

20 In the FSK modulation system, since an error rate is lower when a frequency shift is larger, a filter having a larger nominal frequency shift shows a

better characteristic. Considering the reception side, a filter with strong band limitation on noise has a better S/N and, as a result, has a lower error rate. In the candidate VI, although band limitation on the reception side is strong, since a nominal frequency shift is extremely small, an overall error rate is deteriorated. In the candidate II, since a nominal frequency shift is the second lowest and band limit on the reception side is the loosest, an error rate is also deteriorated. A result obtained by calculating an error rate by applying the nominal frequency shifts of the filters calculated in Expressions (12) to (15) is shown in Figure 10.

According to the result shown in Figure 10, it is proved that the above judgment is correct. The best error rate is indicated when the base band filter of the candidate VII is used. The second best error rate is indicated when the base band filter of the candidate V is used. A C/N is calculated from the result shown in Figure 10 and an error rate with respect to an input level of a receiver at the time when a noise index of the receiver is assumed to be 7 dB is calculated and shown in Figure 11. When it is assumed that a reference sensitivity has an error rate of 3%, in the candidate VII, -122 dBm is an input level at which the reference sensitivity is obtained. The FCC rule provides that a reference sensitivity should be set to 12 dB SINAD when the analog FM modulation system is used in the LMR system applicable to the channel spacing of 12.5 kHz. In a receiver

having a noise index of 7 dB, an input level at which a reception sensitivity of 12 dBSINAD can be obtained is about -120 dBm. When this reception sensitivity of 12 dBSINAD and the candidate VII are compared, as shown in Figure 11, the candidate VII has a sensitivity better than the reception sensitivity by about 2 dB. In the candidate V, the error rate of 3% is obtained by -120.5 dBm. The candidate V has a reference sensitivity equal to that in the case in which the conventional analog FM modulation system is used.

From the above description, a minimum value of a frequency shift for completely adapting a range of actual frequency shifts that can be taken to the mask E is 0.822 kHz indicated by Expression (2) and a maximum value thereof is 0.952 kHz indicated by Expression (4). It is possible to obtain a modulation system conforming to the FCC rule to be enforced in 2005 by calculating nominal frequency shifts of the candidates V and VII using Expressions (9) and (11). On the basis of these facts, embodiments will be explained.

[First Embodiment]

First, a transmission rate, a symbol rate, a base band filter, a modulation system, and a nominal frequency shift in the first embodiment are shown in Table 9 below.

Table 9

Transmission Rate	4800 bps
Symbol Rate	2400 symbol/s
Base Band Filter	Transmission: A filter obtained by combining a filter having a Root Raised Cosine characteristic with an arbitrary $\alpha$ and a filter having a sinc function characteristic Reception: A filter obtained by combining a filter having a Root Raised Cosine characteristic with an arbitrary $\alpha$ and a filter having a $1/\text{sinc}$ function characteristic
Modulation System	Quaternary FSK Modulation System
Nominal Frequency Shift	Arbitrary in ranges $+3=+913$ Hz to $+1057$ Hz and $-3=-913$ Hz to $-1057$ Hz with respect to respective four symbol levels ( $\pm 3, \pm 1$ ) $+1$ and $-1$ are shifts $1/3$ of $+3$ and $-3$ , respectively

Figure 12 is a block diagram showing a constitution of a ground mobile communication system 1 according the first embodiment of the invention. The ground mobile communication system 1 schematically includes a transmitting unit 10 and a receiving unit 20 and performs transmission and reception of data at a transmission rate of 4800 bps.

In the ground mobile communication system 1, as a nominal frequency shift, a predetermined value of  $\pm 913$  kHz to  $\pm 1057$  kHz is set with respect to a symbol level  $\pm 3$  and a value  $1/3$  of the predetermined value is set with respect to a symbol level  $\pm 1$ . This nominal frequency shift is a frequency that shifts when a symbol outputted from a mapper 12 described later is inputted to an FM modulator 14 without intervention of a base band filter 13.



The transmitting unit 10 includes an encoder 11, the mapper 12, the base band filter 13, and the FM modulator 14.

5 The encoder 11 applies predetermined format processing such as encoding processing, error correction code addition processing, and synchronous code addition processing to sound data, character data, and the like to generate a binary signal and supplies the binary signal generated to the mapper 12.

10 The mapper 12 sequentially converts a binary signal sequentially inputted from the encoder 11 into quaternary symbols ( $\pm 3$ ,  $\pm 1$ ) two bits at a time and supplies the quaternary symbols to the base band filter 13. This symbol is a rectangular voltage  
15 signal having a width of a predetermined symbol time. In this embodiment, since a transmission rate is 4800 bps, a symbol rate is 2400 symbol/s and a frequency of a symbol sequence at the time when symbols of  $+3$  and  $-3$  are alternately outputted from the mapper 12 is 1.2  
20 kHz.

The base band filter 13 includes a Nyquist filter. The base band filter 13 blocks a predetermined frequency component of a symbol inputted from the mapper 12 and outputs a waveform signal. In  
25 this embodiment, the base band filter 13 includes a root raised cosine filter 131 and a sinc filter 132.

When a frequency of an inputted rectangular signal is 1.2 kHz, the root raised cosine filter 131 outputs a waveform signal having an amplitude  $\sqrt{2}$  times  
30 as large as that of this rectangular signal. When a

frequency of an inputted rectangular signal is 1.2 kHz, the sinc filter 132 outputs a waveform signal having an amplitude  $2/\pi$  times as large as that of this rectangular signal.

5        In other words, the base band filter 13 in this embodiment shapes a rectangular symbol with a frequency of 1.2 kHz inputted from the mapper 12 into a waveform signal having an amplitude  $2\sqrt{2}/\pi$  times as large as that of the symbol and outputs the waveform  
10    signal.

      The FM modulator 14 shifts a frequency of a signal transmitted to the receiving unit 20 according to a magnitude of an amplitude of a waveform signal outputted from the base band filter 13 to thereby  
15    modulate the frequency (FM modulation).

      To explain the above more in detail, when a level of a symbol outputted from the mapper 12 is +3, the FM modulator 14 shifts a frequency of a signal to be transmitted by  $+\Delta f$  ( $+0.822 \text{ kHz} \leq \Delta f \leq +0.952 \text{ kHz}$ ). When  
20    a symbol level is -3, the FM modulator 14 shifts a frequency of a signal to be transmitted by  $-\Delta f$  ( $-0.822 \text{ kHz} \leq \Delta f \leq -0.952 \text{ kHz}$ ). When a symbol level is +1, the FM modulator 14 shifts a frequency of a signal to be transmitted by  $+\Delta f/3$ . When a symbol level is -1, the  
25    FM modulator 14 shifts a frequency of a signal to be transmitted by  $-\Delta f$ .

      The FM modulator 14 radiates the signal subjected to FM modulation into the air via a not-shown antenna and transmits the signal to the  
30    receiving unit 20.

The receiving unit 20 includes an FM demodulator 21, a base band filter 22, a demapper 23, and a decoder 24.

5 The FM demodulator 21 demodulates a signal inputted and received via a not-shown antenna and supplies a quaternary signal obtained by demodulating the signal to the base band filter 22.

10 The base band filter 22 includes a root raised cosine filter 131 and a  $1/\text{sinc}$  filter 231 having a characteristic opposite to that of the sinc filter 132. The base band filter 22 blocks a predetermined frequency component of a quaternary signal inputted from the FM demodulator 21 and outputs a quaternary signal having an amplitude  $\pi/2\sqrt{2}$  times as large as  
15 that of the input signal.

A Nyquist transmission path is formed in the ground mobile communication system 1 by the base band filter 22 and the base band filter 13 of the transmitting unit 10.

20 The demapper 23 sequentially converts a quaternary signal inputted from the base band filter 22 into a binary signal of 2 bits and supplies the binary signal converted to the decoder 24.

25 The decoder 24 applies decoding processing, error correction processing, and the like to a binary signal supplied from the demapper 23 and outputs sound data, character data, and the like transmitted from the transmitting unit 10.

30 A communication operation of the ground mobile communication system 1 having the constitution

described above will be explained with reference to a flowchart shown in Figure 13.

When sound data, character data, and the like are inputted to the encoder 11 of the transmitting unit 10, the ground mobile communication system 1 starts the communication operation shown in the flowchart in Figure 13.

The encoder 11 applies encoding processing to the sound data, the character data, and the like inputted to generate a binary signal and outputs the binary signal generated to the mapper 12 (step S101).

The mapper 12 applies mapping processing to the binary signal inputted from the encoder 11 to sequentially convert the binary signal into quaternary symbols two bits at a time and outputs the symbols converted to the base band filter 13 (step S102).

The base band filter 13 shapes a waveform signal by applying band limitation processing to the symbols inputted from the mapper 12 to block a predetermined frequency component and outputs the waveform signal shaped to the FM modulator 14 (step S103).

The FM modulator 14 applies FM modulation signal to a transmission signal according to a magnitude of an amplitude of the waveform signal outputted from the base band filter 13 (step S104) and radiates the signal subjected to FM modulation to the air via the not-shown antenna to thereby transmit the sound data, the character data, and the like to the receiving unit 20.

The FM demodulator 21 of the receiving unit 20

applies FM demodulation processing to the signal inputted via the not-shown antenna and received and outputs a quaternary signal obtained by demodulating the signal to the base band filter 22 (step S201).

5       The base band filter 22 applies band limitation processing to the quaternary signal inputted from the FM demodulator 21 and outputs the quaternary signal with a predetermined frequency component blocked to the demapper 23 (step S202).

10       The demapper 23 applies demapping processing to the quaternary signal inputted from the base band filter 22, converts the quaternary signal into a binary signal of 2 bits, and outputs the binary signal converted to the decoder 24 (step S203).

15       The decoder 24 applies decoding processing and the like to the binary signal supplied from the demapper 23 (step S204) to decode the sound data, the character data, and the like transmitted from the transmitting unit 10 and outputs the sound data, the  
20 character data, and the like.

A waveform of an emission spectrum at the time when a nominal frequency shift is set to 1.057 kHz and at the time of the worst condition (when data corresponding to the symbol +3 and data corresponding  
25 to the symbol -3 are alternately inputted to the transmitting unit 10) is shown in Figure 14. An emission spectrum at the time when pseudo-random data is inputted to the transmitting unit 10 is shown in Figure 15.

30 [Second Embodiment]

A second embodiment will be explained. A transmission speed, a symbol rate, a base band filter, a modulation system, and a nominal frequency shift in the second embodiment are shown in Table 10 below.

5

Table 10

Transmission Rate	4800 bps
Symbol Rate	2400 symbol/s
Base Band Filter	Transmission: A filter having a Root Raised Cosine characteristic with an arbitrary $\alpha$ Reception: A filter having a Root Raised Cosine characteristic with an arbitrary $\alpha$
Modulation System	Quaternary FSK Modulation System
Nominal Frequency Shift	Arbitrary in ranges $+3=+581$ Hz to $+673$ Hz and $-3=-581$ Hz to $-673$ Hz with respect to respective four symbol levels ( $\pm 3, \pm 1$ ) $+1$ and $-1$ are shifts $1/3$ of $+3$ and $-3$ , respectively

Figure 16 is a block diagram showing a constitution of a ground mobile communication system 2 according to the second embodiment of the invention. The ground mobile communication system 2 schematically includes a transmitting unit 30 and a receiving unit 40. Components identical with those in the first embodiment are denoted by the identical reference numerals. Explanations of the components are omitted.

In the ground mobile communication system 2, as a nominal frequency shift, a predetermined value of  $\pm 581$  kHz to  $\pm 673$  kHz are set with respect to a symbol level  $\pm 3$  and a value  $1/3$  of the predetermined value is

set with respect to a symbol level  $\pm 1$ .

The transmitting unit 30 includes the encoder 11, the mapper 12, a base band filter 33, and the FM modulator 14. The base band filter 33 includes a root  
5 raised cosine filter 131. The base band filter 33 shapes a rectangular symbol with a frequency of 1.2 kHz inputted from the mapper 12 into a waveform signal having an amplitude  $\sqrt{2}$  times as large as that of the symbol and outputs the waveform signal.

10 The receiving unit 40 includes the FM demodulator 21, a base band filter 42, the demapper 23, and the decoder 24. The base band filter 42 includes a root raised cosine filter 131. The base band filter 42 blocks a predetermined frequency component of a  
15 quaternary signal inputted from the FM demodulator 21 and outputs a quaternary signal having an amplitude  $\sqrt{2}$  times as large as that of the input signal.

As in the ground mobile communication system 1, a Nyquist transmission path is formed in the ground  
20 mobile communication system 2 by the base band filter 42 and the base band filter 33 of the transmitting unit 30.

A waveform of an emission spectrum at the time when a nominal frequency shift is set to 0.673 kHz and  
25 at the time of the worst condition (when data corresponding to the symbol +3 and data corresponding to the symbol -3 are alternately inputted to the transmitting unit 30) is shown in Figure 17. An emission spectrum at the time when pseudo-random data  
30 is inputted to the transmitting unit 30 is shown in

Figure 18.

From the first and second embodiments, in the ground mobile communication systems 1 and 2, even if nominal frequency shifts set are different, frequency shifts of signals actually outputted from the transmitting units 10 and 30 are the same. Thus, the emission spectra shown in Figures 14 and 17 indicate substantially the same characteristics. Since it is possible to confirm that a level of a spectrum is substantially equal to a level calculated from the Bessel function shown in Table 7, it is possible to prove correctness of installation of the ground mobile communication systems 1 and 2. Moreover, as shown in Figures 15 and 18, when pseudo-random data is used, since an emission spectrum has a sufficient room with respect to the standard of the mask E, the ground mobile communication systems 1 and 2 are capable of conforming to the FCC rule to be enforced in 2005.

According to the above description, the quaternary FSK modulation system is applied to the LMR system in this embodiment. Thus, it is possible to directly apply a nonlinear power amplifier and an FM modulation and demodulation circuit of a radio apparatus of analog FM modulation presently operated in the LMR system applicable to the 12.5 kHz channel spacing to the LMR system in this embodiment. Therefore, the LMR system in this embodiment can conform to the FCC rule to be enforced in 2005 without using a linear power amplifier having a problem in terms of cost.



It is possible to handle sound data, character data, and the like all together by applying a modulation system that uses digital data. Thus, the LMR system is suitable for demand for data  
5 communication in these days.

Since it is possible to reduce an error rate while adapting the LMR system to the FCC rule to be enforced in 2005, it is possible to attain a sensitivity equal to or higher than a reference  
10 sensitivity of the conventional analog FM modulation. A call distance is longer compared with the conventional call distance. Moreover, since a transmission power falls when the call distance is the same, it is possible to reduce a consumed current in  
15 the LMR system.

In order to keep downward compatibility, a radio apparatus actually used is required to also implement an operation mode of analog FM modulation used in the LMR system applicable to the 12.5 kHz channel spacing.  
20 However, in the LMR system in this embodiment, since the quaternary FSK modulation system having compatibility with a large number of circuits is adopted, dual mode design is possible. Moreover, the P25-P1 modulation system is based on the quaternary  
25 FSK modulation system, although there is a difference in parameters. Thus, dual mode design in combination with the P25-P1 modulation system is also possible.

The invention is not limited to the embodiments and various modifications and applications of the  
30 embodiments are possible. Modifications of the

embodiments applicable to the invention will be explained.

In the embodiments, the base band filter of the candidate VII is used in the first embodiment and the  
5 base band filter of the candidate V is used in the second embodiment. However, the invention is not limited to these base band filters. The base band filter of the candidate II may be used.

A transmission rate, a symbol rate, a base band  
10 filter, a modulation system, and a nominal frequency shift in the case in which the base band filter of the candidate II is used are shown in Table 11 below.

Table 11

15

Transmission Rate	4800 bps
Symbol Rate	2400 symbol/s
Base Band Filter	Transmission: A filter obtained by combining a filter having a Raised Cosine characteristic with an arbitrary $\alpha$ and a filter having a $1/\text{sinc}$ function characteristic Reception: A filter having a sinc function characteristic
Modulation System	Quaternary FSK Modulation System
Nominal Frequency Shift	Arbitrary in ranges of $+3=+523$ Hz to $+606$ Hz and $-3=-523$ Hz to $-606$ Hz with respect to respective four symbol levels ( $\pm 3, \pm 1$ ) $+1$ and $-1$ are shifts $1/3$ of $+3$ and $-3$ , respectively

Figure 19 is a block diagram showing a constitution of a ground mobile communication system 3 according to a modification of the invention. The

ground mobile communication system 3 schematically includes a transmitting unit 50 and a receiving unit 60. Components identical with those in the first and second embodiments are denoted by the identical reference numerals and explanations of the components are omitted.

In the ground mobile communication system 3, as a nominal frequency shift, a predetermined value of  $\pm 0.523$  kHz to  $\pm 0.606$  kHz are set with respect to a symbol level  $\pm 3$  and a value  $1/3$  of the predetermined value is set with respect to a symbol level  $\pm 1$ .

The transmitting unit 50 includes the encoder 11, the mapper 12, a base band filter 53, and the FM modulator 14. The base band filter 53 includes a root raised cosine filter 531 and a  $1/\text{sinc}$  filter 231. The base band filter 53 shapes a rectangular symbol with a frequency of 1.2 kHz inputted from the mapper 12 into a waveform signal having an amplitude  $\pi/2$  times as large as that of the symbol and outputs the waveform signal.

The receiving unit 60 includes the FM demodulator 21, a base band filter 62, the demapper 23, and the decoder 24. The base band filter 62 includes a sinc filter 132 having a characteristic opposite to that of the  $1/\text{sinc}$  filter 231. The base band filter 62 blocks a predetermined frequency component of a quaternary signal inputted from the FM demodulator 21 and outputs a quaternary signal having an amplitude  $2/\pi$  times as large as that of the input signal.

As in the ground mobile communication systems 1

and 2, a Nyquist transmission path is formed in the ground mobile communication system 3 by the base band filter 62 and the base band filter 53 of the transmitting unit 50 described above.

5       As described above, the base band filter of the candidate II is inferior to the base band filters of the candidates VII and V in terms of a sensitivity but includes the same filter constitution as the base band filter used in the P25-P1 modulation system.  
10       Therefore, it is possible to use a coefficient of a filter that is the same as the base band filter used in the P25-P1 modulation system as long as a roll-off factor  $\alpha$  has the same value as that of the base band filter used in the P25-P1 modulation system. Thus, it  
15       is possible to reduce a circuit size or a memory size.

      In the embodiments, the quaternary FSK modulation system is adopted as a multi-value FSK modulation system. However, the invention is not limited to this. An octonary FSK modulation system, a  
20       hexadecimal FSK modulation system, and the like may be adopted. For example, when the octonary FSK modulation system is used, since a symbol rate is fixed at 2400 symbol/s, a transmission rate is 7200 bps. A symbol level takes eight values of  $\pm 7$ ,  $\pm 5$ ,  $\pm 3$ ,  
25       and  $\pm 1$ . When symbols of  $+7$  and  $-7$  are alternately sent, a sine wave of 1.2 kHz is formed. Therefore, if actual frequency shifts in the symbols of  $+7$  and  $-7$  are set to, for example, the values defined in the first and second embodiments, the modification and the  
30       like, it is possible to adapt an emission spectrum to

the mask E as in the case in which a symbol level takes four values. By adopting such a condition, it is possible to obtain a higher transmission rate by using, other than the octonary FSK modulation system, 5 the hexadecimal FSK modulation system or an FSK modulation system of a larger value while adapting an emission spectrum to the mask E.

In the embodiments, the mobile communication system is the ground mobile communication system. 10 However, the invention is not limited to this. The mobile communication system may be a mobile communication system used on the sea.

#### Industrial Applicability

15 According to the invention, it is possible to provide a modulating apparatus, a ground mobile communication system, a modulating method, and a communication method that can conform to the FCC rule to be enforced in 2005 without using a linear power 20 amplifier.